


Programmable Keypad

PK-1



The Programmable Keypad can be used to adjust or mute the masking and/or paging volume in a defined area of the LogiSon Acoustic Network. Prior to this, the LogiSon Network Administrator will have used the Control Panel or Acoustic Network™ Manager software to establish what area the Keypad controls, what functions are available on it, and the amount by which the user can increase or decrease the volume of the masking or paging. For more information, please see the *LogiSon™ Network Control Panel User Manual* and the *LogiSon™ Acoustic Network™ Manger User Manual*. The Programmable Keypad can be installed in a standard single-gang wall box using a white, Decora-style faceplate.

Control Performance

Functions Masking/paging volume control, masking/paging mute, remote control receiver

Masking Performance

Volume Adjustment Range -99 to +99 (0.5 dBA per increment)
Volume Restriction User-defined maximum and minimum
Function Restriction User able to enable or disable the adjustment function

Paging Performance

Volume Adjustment Range -99 to +99 (0.5 dBA per increment)
Volume Restriction User-defined maximum and minimum
Function Restriction User able to enable or disable the adjustment function

Connections

Network Output 6-pin

Zoning

Method Electronically zoned using Network Control Panel (V 4.1 or later)
Zone Size No limit

Physical Specifications

Dimensions (W x H x D) 4 x 10.4 x 4.6 cm; 1.58 x 4.1 x 1.825 inches
Color White
Weight 120 g; 4.2 oz

Remote Control

Remote Receiver IR remote control receiver for use with PKR-1

Mounting

Methods Single-gang wall box with white, Decora-style faceplate

Programmable Keypad Remote

PKR-1

The Keypad also features a remote control receiver, enabling the user to adjust the Keypad's settings using the Programmable Keypad Remote.

